CrossLink: LIF-MD6000 Master Link Board

This document provides a brief introduction and overview of the CrossLink: LIF-MD6000 Master Link Board, Rev C.

1

Check Kit Contents

The CrossLink: LIF-MD6000 Master Link Board includes the following items:

- LIF-MD6000 Master Link Board
- SMA I/O Link Board
- Breakout I/O Link Board
- USB cable for programming
- 12 V AC adapter power supply
- Quick Start Guide





In addition to general-purpose resources, the board includes two Tx and two Rx connectors on the edges of the board for building CrossLink video bridging solutions. For more information on these and all board features, see the Lattice website at www.latticesemi.com/masterlink.

To develop your own designs, you can use the Lattice Diamond software, available at www.latticesemi.com/diamond.

To re-program the board, you will need Diamond Programmer version 3.7 or later. Diamond programmer can be downloaded from the Lattice web site at www.latticesemi.com/programmer.

2

Check Jumper Settings

JUMPER	DESCRIPTION	DEFAULT SETTINGS
J7	SW2 selector	SHORT 1-2
J16	SPI/I ² C programming selector for LIF-MD6000	SHORT 1-2 (SPI)
J19	SPI Flash chip select	SHORT 1-2
J24	VCCIO1 Bank voltage selector	SHORT 2-3 (3.3 V)
J25	VCCIO2 Bank voltage selector	SHORT 2-3 (3.3 V)
J26	Internal/External clock and I ² C SDA Mux	OPEN

JUMPER	DESCRIPTION	DEFAULT SETTINGS
J27	Internal/External reference clock and I ² C SCL Mux	OPEN
J29	Reset signal voltage selector	OPEN
J35	SPI/I ² C programming selector for LIF-MD6000	SHORT 1-2 (SPI)
J36	SPI/I ² C programming selector for MachXO3LF-1300E	SHORT 1-2 (SPI)
J37	FT2232H reset	OPEN

Note: SW1 is the master power switch. Switch is ON when moved toward the edge of the board.





CrossLink: LIF-MD6000 Master Link Board



Power-up Board and Observe Results

The board is pre-programmed with a basic demonstration, which verifies the board is in working order.

- Connect 12 V adapter to J3 or connect the included USB mini cable from a powered source to connector J2
- Set SW1 to ON (down) position
- Observe the following LEDs

LED	COLOR	MEANING
D3	Green	5 V Power OK
D25	Green	3.3 V Power OK
D29	Green	2.5 V Power OK
D27	Green	1.2 V Power OK
D28	Green	1.8 V Power OK

LED	COLOR	MEANING
D26	Green	12 V Power OK (only lit if 12 V adapter is used)
D6, D7, D8, D9	Blue	CrossLink General Purpose IO CrossLink is programmed
D10	Green	CrossLink CDONE – indicates CrossLink is programmed
LED1, 2, 3, 4	Blue	MachXO3 General purpose IO Default is a sequential pattern
D23	Red	MachXO3 DONE – indicates MachXO3 is programmed

For more information about the CrossLink: LIF-MD6000 Master Link Board, including the Evaluation Board User's Guide, Demonstrations and more, see the Lattice web site at www.latticesemi.com/masterlink.

Additional Terms and Conditions Applicable to Lattice Programming and Development Hardware

Lattice device programmers, programming cables, socket adapters, and other hardware sold for use in conjunction with Lattice software ("Programming Hardware") and Lattice evaluation boards and development kits sold for use in conjunction with evaluating Lattice products ("Development Hardware") are designed and intended for use solely with semiconductor components manufactured by Lattice Semiconductor Corporation. Programming and Development Hardware is warranted to meet Lattice specifications only for a period of ninety (90) days; in all other respects the terms and contitions of sale of Programming and Development Hardware shall be Lattice's standard terms and conditions set forth in Lattice's Sales Order Acknowledgment. Additionally, Lattice specifications for Programming and Development Hardware limit their use to low-volume engineering applications only, and not for volume production use. The warranty for Programming and Development Hardware will not apply to any Programming or Development Hardware used in production, used with worn or improperly installed hardware, or used with incompatible systems or components.

Technical Support

www.latticesemi.com/support

Copyright © 2018 Lattice Semiconductor Corporation. Lattice Semiconductor, L (stylized) Lattice Semiconductor Corp., Lattice (design), Lattice Diamond, Radiant and iCE40 are either registered trademarks or trademarks of Lattice Semiconductor Corporation in the United States and/or other countries. Other product names used in this publication are for identification purposes only and may be trademarks of their respective companies.

QS040 Rev 2 October 2018